



120A Brushless ESC Programmable Options

Programmable Items	Parameter Options								
	1	2	3	4	5	6	7	8	9
1. Battery Type	LiPo	NiMH							
2. Punch	Level 1	Level 2	Level 3	Level 4	Level 5				
3. Brake Force	25%	37%	50%	63%	75%	87.5%	100%		
4. Running Mode	Forward/Reverse w/ Brake	Forward w/ Brake							
5. Motor Rotation	CCW	CW							
6. BEC	6.0V	7.4V							

* The blacked out cells with white text are the default settings.





120 Amp Brushless Smart ESC Specifications

SPMXSE1120

Cont. Current	120A
LiPo Cells	2 - 4S LiPo / 5 - 12S NiMH
BEC Output	6V / 7.4V @ 4A
Size/Weight	43mm x 39mm (54.5mm at tabs) x 33mm/ 153g
Battery Connectors	Dual IC5 (EC5 Compatible) - 12AWG / 165mm (6.5")

Burst Current	830A
Waterproof	IP67 rated
Motor Connector	4mm Female Bullet
Motor Type	Sensorless Brushless
Telemetry	SRXL2 Compatible Spektrum Smart Technology

©2020 Horizon Hobby, LLC. Firma and the Firma logo are trademarks of Horizon Hobby, LLC. The Spektrum trademark is used with permission of Bachmann Industries, Inc.



64341

Spektrum Firma 120 Amp ESC SPMXSE1120

07/20